

SONIFEX

Redbox RB-PA2
Dual Stereo RIAA Phono Amplifier

2014-15
Catalogue





RB-PA2 Dual Stereo RIAA Phono Amplifier



Category: Matching Converters.
Description: Dual Stereo RIAA Phono Amplifier.

Product Function: A record player/turntable pre-amp providing RIAA equalisation.

Typical Applications: Specifically for use with record decks/DJ turntables e.g. for vinyl transfers.

Features: Superbly transparent signal, powerful bass response, Neutrik XLR connectors, adjustable output gain.

The RB-PA2 is a dual stereo RIAA equalised phono amplifier. This record player preamp amplifies the small signal from your pick up cartridge (either moving magnet or high output moving coil magnetic) and provides the necessary RIAA equalisation required for vinyl records, to match it to a line input of your mixer, or amplifier. It uses a clean RIAA response making it ideal for use with broadcast turntables and DJ decks and where vinyl records are being archived to CD for high quality transfers, or for converting albums to mp3.



It operates with phono cartridges with a nominal output of 1mV to 25mV and has been specifically tested to work with the Technics SL-1200™ and 1210™ range of turntables. Quality high specification components have been used together with low noise, fast acting operational amplifiers to produce a superbly transparent signal path. Additionally, the RB-PA2 runs without a rumble filter to produce a powerful bass response.

The RB-PA2 is a dual stereo unit to interface up to two turntables. The inputs are phono connectors with Neutrik XLR connectors for the balanced outputs, which may be wired unbalanced if required. Output gain is individually adjustable for left and right channels in the range 35dB to 65dB by using

pre-set potentiometers. Frequency response is held within 0.5dB of the RIAA curve and noise is typically better than -84dB RMS A weighted at 40dB gain.

Specification For RB-PA2

Audio Specification

Input Impedance:	>47kΩ
Input Sensitivity Range:	1mV to 31mV (ref 1kHz)
Maximum Output Level:	+28dBu
Output impedance:	<50Ω
Output Gain Range:	Adjustable 28dB to 60dB gain via 4 multi-turn pots
Crosstalk:	Better than -80dBu at 1kHz
Frequency Response:	10Hz-15kHz (-3dB)
RIAA Accuracy:	Within 0.5dB of RIAA curve
Distortion:	0.01% THD @ 1kHz, ref +8dBu output
Noise:	-77dB (CCIR Q-Pk, 20Hz-20kHz)

Headroom:	27dB for 3mV input
Dynamic Range:	90dB
Connections	
Analogue Inputs:	4 x RCA Phono sockets.
Analogue Outputs:	4 x XLR 3 pin male (balanced) (L & R)
Earth Tag:	Grounding turret tag
Mains Input:	Filtered IEC, switchable 110-120V, or 220-240V, fused, 6W max.
Fuse Rating:	Anti-surge fuse 100mA 20 x 5mm (230VAC) Anti-surge fuse 250mA 20 x 5mm (115VAC)
Equipment Type	
RB-PA2:	Dual stereo RIAA phono amplifier
Physical Specification	
Dimensions (Raw):	28cm (W) x 10.8cm (D) x 4.2cm (H) (1U) 11" (W) x 4.3" (D) x 1.7" (H) (1U)
Dimensions (Boxed):	36cm (W) x 20.5cm (D) x 6cm (H) 14.2" (W) x 8" (D) x 2.4" (H)
Weight:	Nett: 1.1kg Gross: 1.5kg Nett: 2.4lbs Gross: 3.3lbs

SONIFEX

www.sonifex.co.uk

UK Office:

Sonifex Ltd

61 Station Road, Irthlingborough,

Northants, NN9 5QE, UK

Tel: +44 (0) 1933 650700

Fax: +44 (0) 1933 650726

Email: sales@sonifex.co.uk

Australian Office:

Sonifex Pty Ltd

Unit 12/6 Leighton Place, Hornsby,

New South Wales 2077, Australia

Tel: +61 (2) 9987 0499

Fax: +61 (2) 9476 4950

Email: sales@innescorp.com.au